

ITS323 – Quiz 3

Name: _____ ID: _____ Marks: _____ (10)

Question 1 [3 marks]

The path between SIIT Bangkadi and SIIT Rangsit is measured to have a power loss of 80dB. Both transmit and receive antenna's are identical, with a gain of 12dBi. Using a transmit power of 10dBm, what is the maximum receive power threshold for successful reception? Show your calculations.

Question 2 [3 marks]

You are making a voice call via your computer (e.g. using Skype or similar software). The software, which uses a PCM encoder with 64 code numbers (or levels), generates data at a rate of 60kb/s.

- (a) What is the sampling period used by the encoder? [3 marks]

Question 3 [4 marks]

The following signal was generated using amplitude shift keying. The signalling rate is 1k signal elements per second. The first four bits of data are 0110.

- (a) What are the values of the remaining 6 bits? [4 marks] _ _ _ _ _

Explain your answer.

